



= N 115 .

2/2

Telephone No. 15. The description includes Cord, Flexible, No. 222; Coil, Induction, $\frac{25}{1}$; Switch; Relay, E_1 , 4,000 ohms; Transmitter, Inset; Generator, Bracket, 3-terminal, unmounted; Condenser, m.c., 1 m.f.; Receiver, Bell; and 4 fixing screws and washers.

2 Cells, 2-block, Agglomerate, Complete.

The tags of the Switch are shown as viewed from the back, E_1 being on the left. Switch Positions: Left Position, "Exchange," Keys E_1 and E_2 are actuated. Central Position, "Extension," none of the keys is actuated. Right Position, "Through," Keys T and T_2 are actuated. Plate 52 gives the circuit connections in the various positions of the keys.

Wiring Colours: A Exchange Line, red, R; B Exchange Line, blue, B; A Down Line, red and white, R & W; B Down Line, blue and white, B & W; Speaking Circuit Secondary, yellow, Y; Signalling, green, G.

In earlier patterns of this Instrument the Short Circuit Piece, shown in the diagram in the 4,000-ohms Relay Circuit, was fitted in the circuit of the Trembler Bell.

Page from
1909 Red Book

FIG. 2.—CONNECTIONS OF CIRCUIT.

At the Terminal Office an ordinary C.B.S. Set is fitted, *i.e.*, a Telephone, No. 26; a Telephone, No. 3; or a Telephone, No. 4, with Bell Set No. 5. See Plates 42, 45, and 43 respectively.