

CHARGING CURRENTS  
FOR USE WITH BATTERY UNIT N 634  
& RECTIFIER No. 33 B

N 680

ISSUE A

|                       | SWBDS. AT 3796 & N 1070 |                |                | SWBD. CB 873   |           |                | HOUSE EXCH. SYSTEMS |               |           |              |               |
|-----------------------|-------------------------|----------------|----------------|----------------|-----------|----------------|---------------------|---------------|-----------|--------------|---------------|
|                       | <u>10 + 30</u>          | <u>10 + 50</u> | <u>10 + 60</u> | <u>10 + 30</u> | <u>65</u> | <u>10 + 30</u> | <u>5 + 10</u>       | <u>5 + 20</u> | <u>25</u> | <u>1 + 5</u> | <u>2 + 10</u> |
|                       | <u>65</u>               | <u>65</u>      | <u>180</u>     | <u>10 + 30</u> | <u>65</u> | <u>10 + 50</u> | <u>65</u>           | <u>65</u>     |           |              |               |
|                       |                         |                |                |                |           |                |                     |               |           |              |               |
| CHARGING CURRENT (mA) | 95                      | 115            | 130            | 185            | 200       | 30             | 30                  | 30            | 30        | 30           | 40            |

NOTES -

1. THE MAXIMUM PERMISSIBLE CHARGING CURRENT AT 2.0 VOLTS PER CELL IS 200mA. TO AVOID DAMAGE TO THE RECTIFIER ELEMENT THE TRANSFORMER VOLTAGE TAPS O-60, 10-70, 0-70, MUST NEVER BE USED.
2. THE MINIMUM CHARGING CURRENT TO ENSURE OPERATION OF RELAY 'A' (SEE DIAGRAM N 634/I) IS 30 mA AT 2.2 VOLTS PER CELL.
3. DGM. N 633/I GIVES DETAILS OF ADJUSTMENTS OF SECONDARY TAPPINGS; OTHER INFORMATION IS GIVEN IN EI POWER GENERAL S. 321I.

P.O.E.D.

S. BCH.

PAPER:- Y

CIRCULATION:-

GENERAL

ISSUES

A

B

C

D

E

F

G

H

I

J

K

L

M

N

O

P

Q

R

S

T

U

V

W

X

Y

Z

NEW FORMAT K.M.A.  
T. THINANTE

19-7-66  
25.10.60