

CIRCULATION	GENERAL
	Suffix
Amendt.	
PAPER	W

MAINTENANCE OF TELEPHONE RECEIVERS
CORRECT COMBINATIONS OF RECEIVERS, EARPIECES AND DIAPHRAGMS.
TYPE OF DIAPHRAGM AND EARPIECE TO BE USED WITH RECEIVERS OF VARIOUS PATTERNS

N 690
2 PANELS-1
5-7-49

RECEIVER CODE	DIAPHRAGM No.	EARPIECE No.
RECEIVER, BELL, No. 1A. MARK B	9	1
" " No. 1A. MARKS C, D, AND 4001	12	2
" " No. 1A MARK N.T. 10	18	1
" " No. 4A	12	2
" AND CONDENSERS, HEADGEAR Nos. 1A AND 1F	24	17
" HEADGEAR No. 10A	25	22
" N.T. No. 16, H.C., 40 + 40 OHMS.	12 OR 18	2 OR 9 (NOTE 1)
" INSET No. 1L	12	18
" " No. 2P MARK 1	25	23 (NOTE 2)
" " No. 2P " 2	25	23
" " No. 2P " 3	25	23
" WATCH No. 1B	12	2
" " No. 3D	12	10
" " No. 4D	12	10
" " No. 6L	12	18
" " No. 7P	25	22

NOTES

1. "DIAPHRAGM No.12" MUST BE USED WITH "EARPIECE No.2", AND "DIAPHRAGM No.18" WITH "EARPIECE No.9"
2. RECEIVERS, INSET, No.2P (MARK 1) ARE AT PRESENT FITTED WITH "EARPIECE No.21" BUT THIS EARPIECE WILL BE MADE OBSOLETE WHEN EXISTING STOCKS ARE EXHAUSTED. EARPIECE No.21 IS SUPERSEDED BY EARPIECE No.23. EARPIECE No.21 SHOULD NOT BE FITTED TO RECEIVERS, INSET No. 2P (MARKS 2 AND 3)
3. THE PRECAUTIONS TO BE OBSERVED IN THE MAINTENANCE EXAMINATION OF TELEPHONE RECEIVERS AND THE STEPS TO BE TAKEN TO MAINTAIN RECEIVERS IN AN EFFICIENT CONDITION ARE DESCRIBED IN E.I. TELEPHONES, GENERAL, Z 5020.