



NOTES:-

- 1 Telephone No.740... disconnect transmitter cord from T3 and T10, reconnect to T11 and T12.
Fit Parts 1/DSP/1244 and 1/DBU/372 (engraved 'on') in position 'A'
Fit Parts 1/DST/26 and 1/DBU/372 (engraved 'off') in position 'B'
Set latch bracket of A to position 1.
Set latch bracket of B to position 2.
Part 1/DST/26 is issued as a restoring button only. Connect all spare leads to Part 2/DST/836.
- 2 Rheostat in amplifier to be adjusted when installed, so that a speaker with a weak voice is able to transmit at normal level, as judged by listener at a distant telephone.
- 3 When an extension bell is required, connect in place of Strap A2-A3.
- 4 Ensure that keys on Telephone No.740... are at 'off' position before removing transmitter, otherwise serious damage to amplifier could be caused.

REFERENCES:-

Telecommunications Instruction... C3 B 2135

| APPARATUS SCHEDULE |
|---------------------------------|
| Telephone No.740... |
| Amplifier No.143A |
| Resistor carbon No.91EJ 82 ohms |
| Cord Inst No.12/15AD 3000mm |
| Part 1/DSP/1244 |
| Part 1/DST/26 |
| Part 1/DBU/372 (engraved 'on') |
| Part 1/DBU/372 (engraved 'off') |
| Part 2/DST/836 |

| | | | | |
|--|-------|-------------------------------------|--|----------|
| PO TELECOMMS HQ,RS PAPER:- W DIST:- CB & AUTO | ISSUE | | | |
| | | A | NEW FORMAT. MINOR AMENDMENTS. <i>PJB</i> | TD 7-1-2 |
| | | <input checked="" type="checkbox"/> | T. TROKE | 3-5-61 |

WIRING

