

**CB & AUTOMATIC SYSTEMS**  
**SUBSCRIBER'S EXTENSION PLAN 1A (INTERNAL ONLY) ON INTERNAL**  
**EXTENSION OF PLAN 7 OR 7A USING TELEPHONES Nos.328... & 330...**

N4332  
PAGE 1-2  
ISSUE B

**NOTES**

**GENERAL**

- 1 The diagram shows a Plan 1A Extension connected to the internal Extension of a Plan 7 or 7A. This can be used in conjunction with Dgm N4309 or Dgm N4310.
- 2 Connect Bells No.56A with coils in parallel, these bells and wiring shown dotted at both the Plan 7 internal Extension and the Plan 1A Extension are not required when used in conjunction with Dgm N4309 & should be omitted.

**PLAN 7 OR 7A INTERNAL EXTENSION**

- 3 Recover existing cord, inst a block terminal from Tele No.330... Fit Cord, Inst No.5/14AA & Block, Terminal No.36B & connect Strap BT4-BT5; disconnect wire from T8 at Key Spring 2. Remove strap between T8-T9 & connect Strap T1-T9. Fit Label No.252E on telephone.

**PLAN 1A EXTENSION**

- 4 Fit Cord, Inst No.8/06AA & Block, Terminal No.36B to Tele No.328... Fit Key No.304A with three Parts No.1/SPL/325 (plungers). Set latch bracket control plate of key as shown on Dgm N4301 Fig.6. Remove Straps T10-T11-T12 & add Straps T1-T2-K6-K7; & T12-K8; fit Label No.252F

PO TELECOMMS HQRS  PAPER:- Y  DISTN:- CB & AUTO	ISSUE			
		B NEW FORMAT. MINOR AMENDMENTS. MADE YELLOW <i>ml</i> TD 2-3-1	23-1-74	
		A TELE No.328, K8 WAS SHOWN AS K10	2-5-55	

PLAN 7 OR 7A, EXTENSION

PLAN 1A EXTENSION

