

AUTOMATIC SYSTEMS
SHARED SERVICE SEPARATE METERING
PLAN 4 FACILITIES (INTERNAL ONLY) ON EXTENSION PLAN IA (MAIN)
USING TELEPHONE No. 706..., PLUG No. 505 & JACKS No. 96A

CIRCULATION	C.B. & AUTO
Suffix	
Amendt	
PAPER	W

NOTES :-
1. GENERAL

MORE THAN ONE PORTABLE TELEPHONE MAY BE PROVIDED BUT THE TOTAL NUMBER OF BELLS THAT MAY BE CONNECTED IN SERIES MUST NOT EXCEED FOUR (TWO IN UAX AREAS WITH VIBRATOR RINGING).

2. PLAN IA MAIN
ADDITIONAL APPARATUS REQUIRED:-

PART 1/DSP/1252, CAPACITOR No. 7712-2

CLIP No. 90, CORD INSTRUMENT No. 5/37AA...

RECOVER CORD INST. No. 4/83AA... FIT CLIP No. 90 TO THE RIGHT HAND SWITCH HOOK BRACKET, VIEWED FROM THE BACK, USING THE TWO LOWER HOLES. CAPACITOR No. 7712-2 IS FITTED INTO THE CLIP WITH ITS TAGS POINTING TOWARDS THE REAR OF THE TELEPHONE. FIT PART 1/DSP/1252. FIT CORD INST. No. 5/37AA. REMOVE STRAP T4-T5. CONNECT AS SHOWN. EXTENSIONS PLAN IA ARE CONNECTED AS SHOWN ON DGM. N4522.

3. IF ONLY ONE FIXED TELEPHONE IS REQUIRED

CONNECT THAT INSTRUMENT AS MAIN OF PLAN IA, AS SHOWN, AND STRAP BT1 AND BT5.

4. PLAN 4
APPARATUS REQUIRED

TELEPHONE No. 706., SWITCH No. 5A-3

PART 1/DBU/263, PLUG No. 505 GREY

WITH CORD INST. No. 5/39AD "GREY 723

JACKS No. 96A.

RECOVER CORD INST. No. 3/108AA FROM TELEPHONE No. 706. REARRANGE STRAPS. FIT SWITCH 5A-3 AND PART 1/DBU/263. FIT PLUG No. 505 WITH CORD INST. No. 5/39AD. CONNECT AS SHOWN.

5. AT EACH JACK No. 96 A CONNECT STRAP J1-J5A.

6. AT LAST JACK No. 96 A CONNECT ADDITIONAL STRAP J2-J5.

7. AN EXTENSION BELL MAY BE CONNECTED IN PLACE OF STRAP BT2-BT5 AT PLAN IA MAIN.

N 4540

2 PANELS-2
 PLAN IA MAIN
 DGM. N 4522

USING TELEPHONE No.706... PLUG No. 505 & JACKS No.96A

