

H.E.S. No.3

NON-MULTIPLE EXTENSION
 PLAN 4 (INTERNAL ONLY)
 USING TELEPHONE No.710...



POED. S. BCH. PAPER:- W CIRCULATION GENERAL	ISSUE				
		B	NOTE & AMENDED. MINOR AMENDMENTS.	EW	17-8-70
		A	NEW FORMAT. MINOR AMENDMENTS.	FEIT.	14-2-66
			<i>[Signature]</i> (ISSUE) A	J. H. COMBRIDGE	TD2-3-3

Q428

PAGE 2-3
ISSUE B

NOTES :-

1. FACILITIES OF PLAN 4 ARE SHOWN ON DGM. N1427.
2. APPARATUS REQUIRED
 - 1 BELL SET NO. 26
 - 1 TELEPHONE NO. 710...
 - 1 SWITCH NO. 5A-4
 - 1 PART 22/DBU/260
 - 1 PART 23/DBU/260
 - 1 PART 1/DPL/378
 - 1 PART 1/DPL/379
 - 1 PLUG NO. 505 GREY WITH CORD INST. 5/39 AD GREY 72 IN.
 - 1 THERMISTOR NO. 1A-1JACK NO. 96A AT MAIN AND EACH EXTENSION
1 SWITCH No. 5A-4A. (SEE NOTE 6)
3. CONNECT CORD INST. NO. 5/39 AD GREY 72 IN. TO TELEPHONE NO. 710... AND REARRANGE STRAPS AS SHOWN.
4. WHEN EXTN. BELL IS REQUIRED CONNECT IN PLACE OF STRAP BETWEEN TERMINALS 8 AND 9 OF BELL SET 26, TOTAL NUMBER OF BELLS INCLUDING BELL IN TELEPHONE NO. 710... MUST NOT EXCEED THREE.
5. ONLY ONE TELEPHONE NO. 710... WITH CORD INST. NO. 5/39 AD AND PLUG NO. 505 MAY BE PROVIDED.
6. REMOVE PLUNGERS FROM POSITIONS B AND C, FIT PART 1/DPL/379 IN POSITION B WITH SWITCH 5A-4 (METAL BRACKET TYPE) OR SWITCH 5A-4A. FIT PART 1/DPL/378 (IN POSITION C) WITH SWITCH 5A-4.



7. EXTENSION SWITCH (LOCKING) OPERATES SINGLY TO RETURN LOOP TO THE MAIN STATION. EXCHANGE SWITCH (NON LOCKING) ALSO OPERATES EXTENSION SWITCH CONTACTS PROVIDING EARTHED LOOP CALLING TO SWITCH RELAY UNIT Q 410.
8. ANY SPARE LEADS SHOULD BE SECURED ON SPARE TERMINALS OR ELECTRICALLY INSULATED.

