

UNIVERSAL CONCENTRATOR
DRG. NO. 100999-23 SHEETS

SHEETS

- | | |
|----|---------------------------------|
| 1 | FRONT SHEET |
| 2 | CIRCUIT DETAIL & RECORD SHEET |
| 3 | CIRCUIT CARD |
| 4 | LINE TERMINATION UNIT — GENERAL |
| 5 | " " " — AUTO |
| 6 | " " " — C.B. |
| 7 | " " " — CONTROL |
| 8 | " " " — MAGNETO |
| 9 | " " " — OMNIBUS |
| 10 | " " " — C.B. (SLAVE) |
| 11 | " " " — PARTS LIST |
| 12 | OPERATORS UNIT |

SHEETS

- | | |
|----|---|
| 13 | OPERATORS UNIT PARTS LIST |
| 14 | PLUG-IN MODULES D/T./F & F & KH/F FOR
OPERATORS UNIT |
| 15 | D.T.F. CARD PARTS LIST |
| 16 | F & KH/F CARD PARTS LIST |
| 17 | MODULE DRILLING DETAILS |
| 18 | BRACKET & SPACERS FOR BACKSTRIP MOUNTING |
| 19 | CASE BACK PANEL DRILLING DETAILS |
| 20 | MISCELLANEOUS PARTS LIST |
| 21 | DRILLING DETAILS FOR ADDITIONAL UNITS |
| 22 | PICTORIAL VIEW OF EXTN. CARD & SOCKET |
| 23 | S.T.C. CONTROL ARRANGEMENTS |

NOTE: FOR CONCENTRATORS SUPPLIED TO THE SCOTTISH REGION WITH THE ADDITIONAL
"RESTORE KEY ALARM" FACILITY ON THE OPERATORS UNIT SEE DRG. 100309 SHEET 2
(WITH RESTORE KEY ALARM)

DRAWN BY	K.H.	J.F.
CHECKED BY	K.H.	cm
ASST. TEL. ENG.	ON	
CORR. REF.	TS 1153/3A	
AUTHORITY		
DATE		
H. O. BALDWIN <i>for Baldwin</i>		
CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER		

BRITISH RAILWAYS		E. REGION	
CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEERS OFFICE, YORK.			
UNIVERSAL CONCENTRATOR			
FRONT SHEET			
DRAWING No		ISSUE	
100999		1 2	
SHEET 1 OF 23 SHEETS			

[illegible]

OMNIBUS	ABCD
LOOP	L
25 HZ	~
CONTROL	W\$

SUPERSEDED BY ISSUE 3 26/6/76

THIS CARD IS FOR COMPLETION BY HAND WITH THE CALLING CODES FOR OMNIBUS CIRCUITS APPEARING ON THE CONCENTRATOR
IT FITS IN THE DRAWER BELOW THE FRONT PANEL

CIRCUIT CARD FOR

TO CALL PUSH THE RING POSITION BUTTON FOR THE CIRCUIT CONCERNED THEN CODE A,B,C,D OR F
AS REQUIRED AND RESTORE THE RING POSITION BUTTON BEFORE SPEAKING.

ISSUE		App.	COMP.	DRN.	K.H. J.F.	Chkd.	K.H.	BRITISH RAILWAYS		E. REGION	
1	—	—	—	ASSY. TELECOMMS ENGINEER		C.W.		CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER'S OFFICE, YORK			
2	REDRAWN WAS PREVIOUSLY DRG. No. 100309 SHT. G			CORR. REF.		TS1153/3A		CIRCUIT CARD FOR UNIVERSAL CONCENTRATOR			
				AUTHORITY							
				DATE							
				H. O. BALDWIN <i>for Ollivall</i> Chief Signal and Telecommunications Engineer				SHEET 3 OF 24 SHEETS			
								DRG. No. 100999			
								ISSUE			
								1 2			

- NOTES
- (1) ALL RELAYS TO BE DRY REED SWITCH TYPE AS SHOWN ON PARTS LIST.
 - (2) STRAPS 45-46 & 48-49 TO BE NORMALLY IN. IF 'B' OPERATOR IS BARRED OUT STRAPS 45-46 & 48-49 AND STRAP 45-47 & 48-50.
 - (3) ALL RESISTOR VALUES ARE IN OHMS.
 - (4) ALL CAPACITOR VALUES ARE IN MICROFARADS.
 - (5) FOR OMNIBUS WORKING STRAP FROM 2 TO NEXT PIN WITH 2.7 ZENER DIODE & 3 TO NEXT PIN WITH 2.7 ZENER DIODE. THE CATHODE (OR WHITE BAND) ON ZENER TO CO ON 2 & 3.




FIG. 3

STRAPPINGS TO PREVIOUS & SUBSEQUENT COPPER STRIPS AT BACK OF CONCENTRATOR, EXPLANATORY ONLY. SEE DRC N° 100999 SHT. 2.

BARRIER STRIP

L1

D V

T(A)PK F V

T(A)SK H V

T(B)PK J V

T(B)SK K V

BARRIER STRIP

L2

E V

R(A)PK L V

R(A)SK M V

R(B)PK N V

R(B)SK P V

MOUNTED ON BACK STRIP

470

1W

470




1W

L(A)PK AK V

L(A)SK AE V

L(B)PK AN V

L(B)SK AF V



DRAWN BY K.H. J.F.

CHECKED BY K.H. J.F.

ASST. TEL. ENG. J.F.

CORR. REF. TS1153/3A

AUTHORITY

DATE

H. O. BALDWIN

CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER

BRITISH RAILWAYS E. REGION

CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEERS OFFICE, YORK.

LINE TERMINATION UNIT

FOR

UNIVERSAL CONCENTRATOR


GENERAL

DRAWING No 100999

SHEET 4 OF 23 SHEETS

ISSUE 1 2

- NOTES
- (1) ALL RELAYS TO BE DRY REED SWITCH TYPE AS SHOWN ON PARTS LIST.
 - (2) STRAPS 45-46 & 48-49 TO BE NORMALLY IN. IF 'B' OPERATOR IS BARRED CUT STRAPS 45-46 & 48-49 AND STRAP 45-47 & 48-50.
 - (3) ALL RESISTOR VALUES ARE IN OHMS.
 - (4) ALL CAPACITOR VALUES ARE IN MICROFARADS.
 - (5) FOR OMNIBUS WORKING, STRAP FROM 2 TO NEXT PIN WITH 2.7 ZENER DIODE & 3 TO NEXT PIN WITH 2.7 ZENER DIODE. THE CATHODE (OR WHITE BAND) ON ZENER TO CP ON 2 & 3.



FOR AUTO TERMINATION AS SHOWN IN FIG.1, THE CIRCUIT STRAPPINGS ARE AS FOLLOWS:-
PINS: 1-2, 53-4-5-6, 22-26, 25-27-29, 30-31, 33-35, 8-9-11-3

FIG.3

STRAPPINGS TO PREVIOUS & SUBSEQUENT COPPER STRIPS AT BACK OF CONCENTRATOR, EXPLANATORY ONLY. SEE DRC N° 100999 SHT. 2.

BARRIER STRIP

L1

D V

T(A)PK F V

T(A)SK H V

T(B)PK J V

T(B)SK K V

BARRIER STRIP

L2

E V

R(A)PK L V

R(A)SK M V

R(B)PK N V

R(B)SK P V

MOUNTED ON BACK STRIP

470 1W




470 1W

L(A)PK AK V

L(A)SK AE V

L(B)PK AN V

L(B)SK AF V



DRAWN BY K.H. J.F.

CHECKED BY K.H. J.F.

ASST. TEL. ENG. J.F.

CORR. REF. TS1153/3A

AUTHORITY

DATE

H. O. BALDWIN

CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER

BRITISH RAILWAYS E. REGION

CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEERS OFFICE, YORK.

LINE TERMINATION UNIT

FOR

UNIVERSAL CONCENTRATOR


(AUTO)

DRAWING No 100999



SHEET 5 OF 23 SHEETS

ISSUE 1

- (1) ALL RELAYS TO BE DRY REED SWITCH TYPE AS SHOWN ON PARTS LIST.
- (2) STRAPS 45 - 46 & 48 - 49 TO BE NORMALLY IN.
IF 'B' OPERATOR IS BARRED CUT STRAPS 45 - 46 & 48 - 49 AND STRAP 45 - 47 & 48 - 50.
- (3) ALL RESISTOR VALUES ARE IN OHMS.
- (4) ALL CAPACITOR VALUES ARE IN MICROFARADS
- (5) FOR OMNIBUS WORKING STRAP FROM 2 TO NEXT PIN WITH 2.7 ZENER DIODE & 3 TO NEXT PIN WITH 2.7 ZENER DIODE.
THE CATHODE (OR WHITE BAND) ON ZENER TO QO ON 2 & 3



STRAPPINGS TO PREVIOUS
& SUBSEQUENT COPPER
STRIPS AT BACK OF
CONCENTRATOR,
EXPLANATORY ONLY. SEE
DRG. NO. 100999 SHT. 2.






BACK STRIP

470 1W L(A)PK AK V





470 1W L(A)SK AE V

470 1W L(B)PK AN V

470 1W L(B)SK AF V



OPERATORS UNIT EXPLANATORY
ONLY. SEE DRG N° 100999 SHT 12, FIG 1.




H. O. BALDWIN
H. O. Baldwin

CHIEF SIGNAL & TELECOMMUNICATIONS
ENGINEER

ISSUE		APP	COMPLETED
1	—	—	
2	REDRAWN WAS PREVIOUSLY DRG. NO 100309 SHT 1		

BRITISH RAILWAYS		E. REGION	
CHIEF TELEGRAPH & TELECOMMUNICATIONS ENGINEERS OFFICE, YORK.			
<u>LINE TERMINATION UNIT</u>			
<u>FOR</u>			
<u>UNIVERSAL CONCENTRATOR</u>			
<u>(C.B.)</u>			
DRAWING No		ISSUE	
1000000		1	2
SHEET 6 OF 23 SHEETS			

- NOTES
- (1) ALL RELAYS TO BE DRY REED SWITCH TYPE AS SHOWN ON PARTS LIST.
 - (2) STRAPS 45-46 & 48-49 TO BE NORMALLY IN. IF 'B' OPERATOR IS BARRED CUT STRAPS 45-46 & 48-49 AND STRAP 45-47 & 48-50.
 - (3) ALL RESISTOR VALUES ARE IN OHMS.
 - (4) ALL CAPACITOR VALUES ARE IN MICROFARADS.
 - (5) FOR OMNIBUS WORKING, STRAP FROM 2 TO NEXT PIN WITH 2.7 ZENER DIODE & 3 TO NEXT PIN WITH 2.7 ZENER DIODE. THE CATHODE (OR WHITE BAND) ON ZENER TO CO ON 2 & 3.



FOR CONTROL TERMINATION AS SHOWN IN FIG.1, THE CIRCUIT STRAPPINGS ARE AS FOLLOWS:-
PINS: 1(20K)2, 53-5, 6-9, 3-11, 10-14, 17-18, 19-20, 13-36-35-30, 25-32, 27-29, 24-26, 37-39, 40-42 (WS WIRE TO PROVIDE A -VE)

FIG.3

STRAPPINGS TO PREVIOUS & SUBSEQUENT COPPER STRIPS AT BACK OF CONCENTRATOR, EXPLANATORY ONLY. SEE DRC NO 100999 SHT 2.

BARRIER STRIP

L1

D V

T(A)PK F V

T(A)SK H V

T(B)PK J V

T(B)SK K V

BARRIER STRIP

L2

E V

R(A)PK L V

R(A)SK M V

R(B)PK N V

R(B)SK P V

MOUNTED ON BACK STRIP

470 1W

470 1W

L(A)PK AK V

L(A)SK AE V

L(B)PK AN V

L(B)SK AF V












FIG.2

OPERATORS UNIT EXPLANATORY ONLY. SEE DRC NO 100999 SHT 12, FIG.1.



DRAWN BY K.H. J.F.

CHECKED BY K.H. J.F.

ASST. TEL. ENG.

CORR. REF. TS1153/3A

AUTHORITY

DATE


H. O. BALDWIN

CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER

ISSUE		APP	COMPLETED
1			
2	REDRAWN WAS PREVIOUSLY DRC NO 100309 SHT 1		

BRITISH RAILWAYS E. REGION	
CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEERS OFFICE, YORK.	
LINE TERMINATION UNIT	
FOR	
UNIVERSAL CONCENTRATOR	
CONTROL	
DRAWING No	ISSUE
100999	1 2
SHEET 7 OF 23 SHEETS	













- NOTES
- (1) ALL RELAYS TO BE DRY REED SWITCH TYPE AS SHOWN ON PARTS LIST.
 - (2) STRAPS 45-46 & 48-49 TO BE NORMALLY IN. IF 'B' OPERATOR IS BARRED OUT STRAPS 45-46 & 48-49 AND STRAP 45-47 & 48-50.
 - (3) ALL RESISTOR VALUES ARE IN OHMS.
 - (4) ALL CAPACITOR VALUES ARE IN MICROFARADS.
 - (5) FOR OMNIBUS WORKING, STRAP FROM 2 TO NEXT PIN WITH 2.7 ZENER DIODE & 3 TO NEXT PIN WITH 2.7 ZENER DIODE. THE CATHODE (OR WHITE BAND) ON ZENER TO CP ON 2 & 3.



FOR MAGNETO TERMINATION AS SHOWN IN FIG.1, THE CIRCUIT STRAPPINGS ARE AS FOLLOWS:-
PINS: 1-2, 53-4-5-6, 8-9-11-12, 10-14, 17-18, 19-20, 37-39, 40-42, 3-7, 33-35-36, 24-26, 25-27-29, 30-31, 53(22K)3

FIG.3

STRAPPINGS TO PREVIOUS & SUBSEQUENT COPPER STRIPS AT BACK OF CONCENTRATOR, EXPLANATORY ONLY. SEE DRC NO 100999 SHT. 2.




ISSUE		APP	COMPLETED
1			
2	REDRAWN WAS PREVIOUSLY DRC NO 100309 SHT 1		

BRITISH RAILWAYS		E. REGION	
CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEERS OFFICE, YORK.			
LINE TERMINATION UNIT			
FOR			
UNIVERSAL CONCENTRATOR			
(MAGNETO)			
DRAWING No		ISSUE	
100999		1 2	
SHEET 8 OF 23 SHEETS			

DRAWN BY	K.H.	J.F.
CHECKED BY	K.H.	J.F.
ASST. TEL. ENG.		
CORR. REF.	TS1153/3A	
AUTHORITY		
DATE		

H. O. BALDWIN	
CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER	

- NOTES
- (1) ALL RELAYS TO BE DRY REED SWITCH TYPE AS SHOWN ON PARTS LIST.
 - (2) STRAPS 45-46 & 48-49 TO BE NORMALLY IN. IF 'B' OPERATOR IS BARRED OUT STRAPS 45-46 & 48-49 AND STRAP 45-47 & 48-50.
 - (3) ALL RESISTOR VALUES ARE IN OHMS.
 - (4) ALL CAPACITOR VALUES ARE IN MICROFARADS.
 - (5) FOR OMNIBUS WORKING, STRAP FROM 2 TO NEXT PIN WITH 2.7 ZENER DIODE & 3 TO NEXT PIN WITH 2.7 ZENER DIODE. THE CATHODE (OR WHITE BAND) ON ZENER TO CP ON 2 & 3.



FOR OMNIBUS TERMINATION AS SHOWN IN FIG.1, THE CIRCUIT STRAPPINGS ARE AS FOLLOWS:-

TO RECEIVE A 'A' RING:- 2-4, 8-9, 5-11, 3-6

" " " "B" :- 2-8, 4-9, 5-6, 3-11

" " " "C" :- 2-8, 4-9, 5-11, 15, 3-12, 6-7






" " " "D" :- 2-4, 8-9, 5-11, 15, 3-7, 6-12

COMMON TO 'A', 'B', 'C', 'D'

18-34, 19-25-35, 26-28, 27-29, 37-39, 40-42, 43-44, 32-52, 30-33-51

FIG.3

STRAPPINGS TO PREVIOUS & SUBSEQUENT COPPER STRIPS AT BACK OF CONCENTRATOR, EXPLANATORY ONLY. SEE DRC N° 100999 SHT. 2.



ISSUE		APP	COMPLETED
1			
2	REDRAWN WAS PREVIOUSLY DRC N° 100309 SHT 1		

DRAWN BY K.H. J.F.
CHECKED BY K.H. J.F.
ASST. TEL. ENG. J.F.
CORR. REF. TS1153/3A
AUTHORITY
DATE

H. O. BALDWIN
CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER

BRITISH RAILWAYS E. REGION
CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEERS OFFICE, YORK.

LINE TERMINATION UNIT
FOR
UNIVERSAL CONCENTRATOR
(OMNIBUS)

DRAWING No 100999
SHEET 9 OF 23 SHEETS

ISSUE 1 2

NOTES

- (1) ALL RELAYS TO BE DRY REED SWITCH TYPE AS SHOWN ON PARTS LIST.
- (2) STRAPS 45 - 46 & 48 - 49 TO BE NORMALLY IN. IF 'B' OPERATOR IS BARRED CUT STRAPS 45 - 46 & 48 - 49 AND STRAP 45 - 47 & 48 - 50.
- (3) ALL RESISTOR VALUES ARE IN OHMS.
- (4) ALL CAPACITOR VALUES ARE IN MICROFARADS
- (5) FOR OMNIBUS WORKING STRAP FROM 2 TO NEXT PIN WITH 2-7 ZENER DIODE & 3 TO NEXT PIN WITH 2 7 ZENER DIODE.

THE CATHODE (OR WHITE BAND) ON ZENER TO CO OR 2 & 3

- KEY BACKVIEW

ERROR CORRECTED, 14-17 NOT STRAPPED
SH, 2008

FIG. 3
STRAPPINGS TO PREVIOUS
& SUBSEQUENT COPPER
STRIPS AT BACK OF
CONCENTRATOR,
EXPLANATORY ONLY. SEE
DRG. NO 1009999 BHT. 2.

BARRIER
STRIP

LI

T(A)Pr

T(A)Sk

T(B)Pr

T(B)Sk

BARRIER
STRIP

L2

R(A)PK

R(A)SK

R(B)PK


R(B)SK

MOUNTED ON
BACK STRIP

470
1W

470
1W

L(A)PK
L(A)SK
L(B)PK
L(B)SK



DRAWN BY	K.H.	J.F.
CHECKED BY	K.H.	CSM
ASST. TEL. ENG.	ON	
CORR. REF.	TS1153/3A	
AUTHORITY		
DATE		

H. O. BALDWIN

for [Signature]

CHIEF SIGNAL & TELECOMMUNICATIONS
ENGINEER


BRITISH RAILWAYS E. REGION
CHIEF SIGNAL & TELECOMMUNICATIONS
ENGINEERS OFFICE, YORK.

LINE TERMINATION UNIT
FOR
UNIVERSAL CONCENTRATOR
(C. B. SLAVE)

DRAWING No	ISSUE					
100000	<table border="1" style="display: inline-table; border-collapse: collapse;"> <tr> <td style="width: 20%; text-align: center; padding: 5px;">1</td> <td style="width: 20%; text-align: center; padding: 5px;">2</td> <td style="width: 20%;"></td> <td style="width: 20%;"></td> <td style="width: 20%;"></td> </tr> </table>	1	2			
1	2					
SHEET 10 OF 23 SHEETS						

NOTES

ALL RESISTOR VALUES ARE IN OHMS.
ALL CAPACITORS VALUES ARE IN MICROFARADS UNLESS OTHERWISE STATED.
THE FUSE ON THE 254Z RINGER WILL BE 1A ON THIS UNIT AND NOT 750mA AS STATED ON DRG. NO. 64-YT-109




TO PLUG IN DELAY/TONE/
FLASH CARD TO DRG. NO.
100999 SHT. 14

TO PLUG IN F & KH/F CARD
TO DRG. NO. 100999 SHT. 14

FIG. A PART OF PLUG IN
F & KH/F CARD DRG. NO.
100999 SHT. 14.

FIG. 2 (LINE TERMINATION UNIT)
EXPLANATORY ONLY SEE DRG. NO.
100999 SHT. 4, FIG. 1



DRAWN BY	K.H.	J.F.
CHECKED BY	K.H.	CA
ASST. TEL. ENG.		
CORR. REF.	TS1153/3A	
AUTHORITY		
DATE		
H. O. BALDWIN		
CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER		

<u>BRITISH RAILWAYS</u>		<u>E. REGION</u>	
<u>CHIEF SIGNAL & TELECOMMUNICATIONS</u>			
<u>ENGINEERS OFFICE, YORK.</u>			
<u>OPERATORS UNIT</u>			
<u>FOR</u>			
<u>UNIVERSAL CONCENTRATOR</u>			
DRAWING No		ISSUE	
100899		1	2
SHEET 12 OF 23 SHEETS			

ITEM No.	QTY.	DESCRIPTION	REF. DRG. CAT. No. ETC.
1	1	4" MODULE EXTRA VOLUME	VEROPb. N° 1A/VMU/7EU/4/A
2	1	6"x8" VEROBOARD 0.1x0.1 MATRIX	" " 314
3	4	SADDLE WASHERS	" " 4112
4	4	" "	" " 4110
5	2	EDGE CONNECTORS 0.1 MATRIX 24 OUTLET	" " 2233/1
6	2	TMC PUSHES NON LOCK 2C/O	B.R. CODE 990-654-1
7	3	" " " " 3C/O	" " 990-654-2
8	2	" " LOCKING 4C/O	" " 990-654-4
9	2	INDUCTION COILS B.P.O. 31	" " 990-96-19
10	2	CAPACITORS 1.8µf + 0.9µf B.P.O. 7719	" " 990-186-21
11	2	TELE. JACKS B.P.O. 84	" " 990-904-20
12	2	" PLUGS B.P.O. 420	" " 990-904-21
13	2	CARBON RESISTORS 150Ω 1W	" " 990-9-2
14	2	" " 39Ω 1W	" " 990-9-1
15	2	P.O. 3000 TYPE RELAY (1A) 200+200 3NI HIGH IMP. B.P.O. CODE 33900451	" " 990-239-42
16	1	DIAL WITH N° ENGRAVED & PAPER	USUAL SUPPLIERS
17	1	RINGING GENERATOR COMPLETE WITH CHOKE	" "
18	2	TELE. HANDSETS (DELTA LINE) B.P.O. 10A WITH CORD. 1 DOLPHIN BLUE, 1 HERON GREY	" "
19	1	RESISTOR 1.8KΩ 5W	RADIO SPARES
20	2	" 150Ω 10W	"
21	1	" 100Ω 10W	"
22	1	CAPACITOR 320µf ELECTROLYTIC 64V WKG.	"
23	1	MINIATURE PANEL HOLDER (20mm)	"
24	1 PACK 10	GLASS FUSES (20mm) 1A	"
25	1	0.5Ω RETARD COIL	"
26	1	5D4 DIODES (1R)	FARNELL
27	1	B.P.O. 1000 TYPE LEVER KEY 2C/O + 2K LOCKING 2C/O + 2K LOCKING	"
28	2	RECTIFIER SELENIUM CLICK SUPPRESSOR FSX 5A (P.O. N° 205)	S.T.C.
29	2	50Ω WELWYN RESISTOR (W24)	

FOR CONCENTRATORS FITTED WITH RESTORE KEY ALARM FACILITIES
THE FOLLOWING ITEMS ARE REQUIRED


1	1	1B L.H. SPRINGSET	
2	1	1B R.H. "	

FOR CONCENTRATORS FITTED WITH RESTORE KEY ALARM FACILITIES, ITEM N° 18 ABOVE


IS CHANGED TO 2 HANDSETS WITH PRESSEL SWITCH

ISSUE		App	COMP	DRN.	K.H. J.F.	Ch'd	KH CH	BRITISH RAILWAYS		E. REGION	
1				ASST. TELECOMMS. ENGINEER		CH		CHIEF SIGNAL & TELECOMMUNICATIONS			
2 REDRAWN WAS PREVIOUSLY DRG. N° 100309 BHT. 2A.				CORR. REF		TS1153/3A		ENGINEER'S OFFICE, YORK			
				AUTHORITY				UNIVERSAL CONCENTRATOR			
				DATE				OPERATOR MODULE			
				H. O. BALDWIN				EXCLUDING KH/F CARD & T/F/D CARD			
				for (Signature)				PARTS SCHEDULE			
				Chief Signal and Telecommunications Engineer				SHEET 13 OF 23 SHEETS		ISSUE	
								DRG. No. 100999		1 2	

EDGE CONNECTOR
MOUNTED ON
OPERATORS UNIT



DELAY/TONE/FLASH UNIT



NOTES

- 1 DELAY, TONE & FLASH TO BE MOUNTED ON A PRINTED CIRCUIT CARD THIS CARD WILL PLUG INTO THE OPERATORS MODULE ON THE UNIVERSAL CONCENTRATOR.
- 2 F & KH CARD TO BE MOUNTED AS ABOVE.
- 3 ALL RESISTOR VALUES ARE IN OHMS.
- 4 ALL CAPACITOR VALUES ARE IN MICROFARADS UNLESS OTHERWISE STATED.

ZTX 502 & 302

C E E

F, LA
& DL

RED REED RELAY
FOR 500Ω WORKING STRAP a-e



FOR 2000Ω WORKING STRAP b-e
VIEW FROM BACK OF RELAY

THYRISTOR
CAC BEVEL

KH/F

FOR 2000Ω WORKING STRAP b-d

FIG. A' ON
DRG. NO.
100999
6HT.12



DRAWN BY K.H. J.F.
CHECKED BY K.H. J.F.
ASST. TEL. ENG. J.F.
CORR. REF. TS1153/3A
AUTHORITY
DATE


H. O. BALDWIN
CHIEF SIGNAL & TELECOMMUNICATIONS
ENGINEER

BRITISH RAILWAYS E. REGION
CHIEF SIGNAL & TELECOMMUNICATIONS
ENGINEERS OFFICE, YORK.
PLUG-IN MODULES
FOR OPERATORS UNIT
ON THE
UNIVERSAL CONCENTRATOR

DRAWING No. 100999
SHEET 14 OF 23 SHEETS

ISSUE 1 2

ITEM No.	QTY.	DESCRIPTION	REF. DRG. CAT. No. ETC.
1	4	RESISTORS CARBON 2.2K Ω $\frac{1}{2}$ W.	RADIO SPARES
2	2	" " 33K	"
3	3	" " 22K	"
4	4	" " 10K	"
5	1	" " 3.9K	"
6	1	" " 2.7K	"
7	1	" " 27K	"
8	2	" " 1K	"
9	2	" " 220	"
10	1	" " 470 Ω	"
11	1	" " 3.3K	"
12	1	" " 6.8K	"
13	1	" " 68K	"
14	1	" " 1K 1W	"
15	1	" " 560 1W	"
16	1	" " 1.2K 1W	"
17	1	" " 2.2K 1W	"
18	2	CAPACITORS 32 μ F 15V ELECTROLYTIC SUB MIN	RADIO SPARES
19	2	" 0.01 μ F 500V AC MINIATURE TUB	"
20	1	" 10 μ F 63V POLYCARBONATE	"
21	2	" 0.1 μ F 250V DC POLYESTER	"
22	2	" 1 μ F 250V DC POLYESTER	"
23	1	" 500 μ F 25V DC ELECTROLYTIC	"
24	4	" 6 μ F 15V DC ELECTROLYTIC	"
25	3	12V ZENER DIODES BZY 95/C12	FARNELL
26	2	TRANSISTORS 2TX 302	FERRANTI
27	6	" 2TX 502	"
28	2	THYRISTORS GE C106B1	JERMYN
29	1	TONE/FLASH/DELAY PRINTED CCT. BD.	C.S.P.K.
30	1	D.L. REED RELAY CD 1723	OSMOR RELAYS
31	6	5D4 DIODES	FARNELL

ISSUE		App	COMP.	DRN.	K.H. J.F.	Chkd.	K.H. J.F.
1							
2	REDRAWN WAS PREVIOUSLY DRG. No. 100309 SHT. 3A			ASST. TELECOMMS. ENGINEER		TS1153/3A	
				CORR REF			
				AUTHORITY			
				DATE			
				H.O. BALDWIN			
				 Chief Signal and Telecommunications Engineer			

BRITISH RAILWAYS		E. REGION	
CHIEF SIGNAL & TELECOMMUNICATIONS			
ENGINEER'S OFFICE, YORK			
UNIVERSAL CONCENTRATOR			
TONE/FLASH/DELAY CARD			
PARTS SCHEDULE			
SHEET 15		OF 23	SHEETS
DRG. No. 100999		ISSUE	
		1	2


NB: IT IS NOT CLEAR WHY THIS IS SHEET 15A, AS IT APPEARS SIMPLY TO BE A LATER REVISION OF SHEET 15 - SH, 2008

ITEM No.	QTY.	DESCRIPTION	REF. DRG. CAT. No. ETC.
1	4	RESISTORS CARBON 2.2K Ω $\frac{1}{2}$ W.	RADIO SPARES
2	2	" " 33K	"
3	3	" " 22K	"
4	4	" " 10K	"
5	1	" " 3.9K	"
6		" " 2.2K 1W	"
7		" " 27K	"
8	2	" " 1K	"
9	2	" " 220	"
10	1	" W/W 56 2.5W	"
11	1	" CARBON 3.3K	"
12	1	" " 6.8K	"
13	1	" " 68K	"
14	1	" " 1K 1W	"
15	1	" " 560 1W	"
16	1	" W/W 500 5W	"
17	1	CAPACITORS 47 μ F 63V ELECTROLYTIC	"
18	2	" 32 μ F, 63V ELECT.	UNITED ELECTRONICS
19	2	" 0.01 μ F 500VAC MINIATURE TUB	RADIO SPARES
20	1	" 10 μ F 63V POLYCARBONATE	"
21	2	" 1 μ F 250VDC POLYESTER	"
22	1	" 22 μ F 16VDC TANTALUM	"
23	1	" 500 μ F 25VDC ELECTROLYTIC	"
24	4	" 6 μ F 15VDC ELECTROLYTIC	"
25	1	TRANSISTOR MPSU95	JERMYN
26	2	TRANSISTORS ZTX 302	FERRANTI
27	5	" ZTX 502	"
28	2	THYRISTORS CE C106BI	JERMYN
29	1	TONE/FLASH/DELAY PRINTED CCT. BD.	G.S.P.K.
30	1	D.L. REED RELAY CD 1723	OSMOR RELAYS
31	2	504 DIODES	FARNELL
32	2	12V ZENER DIODES BZY95/C12	"
33	1	6.2V " " BZY96/C6V2	"
34	2	$\frac{3}{4}$ " PTFE 1m.m. SLEEVE HELATEMP 300	HELLERMAN


ISSUE	App	COMP.	DRN.	K.H. J.F.	Chkd.	K.H. J.F.
1						
2				ASST. TELECOMMS. ENGINEER		
				CORR REF	TS1153/3A	
3				AUTHORITY		
				DATE		
4				H.O. BALDWIN		
				Chief Signal and Telecommunications Engineer		

BRITISH RAILWAYS E. REGION
CHIEF SIGNAL & TELECOMMUNICATIONS
ENGINEER'S OFFICE, YORK
UNIVERSAL CONCENTRATOR
TONE/FLASH/DELAY CARD
PARTS SCHEDULE

SHEET 15A OF 24 SHEETS
DRG. No. 100999
ISSUE
1 2



FRONT VIEW (LINE TERM. UNIT)
(FRONT PANEL)



FRONT VIEW (OPERATORS)
(FRONT PANEL)

SCALE :- FULL SIZE



DRAWN BY	K.H.	J.F.
CHECKED BY	K.H.	CH
ASST. TEL. ENG.	CH	
CORR. REF.	TS1153/3A	
AUTHORITY		
DATE		

H. O. BALDWIN
H. O. Baldwin
CHIEF SIGNAL & TELECOMMUNICATIONS
ENGINEER

BRITISH RAILWAYS E. REGION
CHIEF SIGNAL & TELECOMMUNICATIONS
ENGINEERS OFFICE, YORK.
UNIVERSAL CONCENTRATOR
MODULE DRILLING DETAILS


DRAWING No	ISSUE
100999	1 2
SHEET 17 OF 23 SHEETS	

ISSUE	APP	COMPLETED
1		
2		
REDRAWN WAS PREVIOUSLY DRG. No 100309 SHT. 4.		



TAPPED GBA.

SCALE: FULL SIZE





ADITS

SPACER


EDGE
CONNECTOR

2 BRACKETS PER CASE REQD.		
TOTAL LENGTHS :-	1) 16" CASE WITH OPERATORS UNIT	" -12 3/4"
2) 16" "	" WITHOUT	" -15 3/4"
3) 8" "	" "	" -7 3/4"

ISSUE		APP	COMP.	DRN.	K.H. J.F.	Chkd	KH <i>ESL</i>	BRITISH RAILWAYS		E REGION
1	—	—	—	ASSY. TELECOMMS ENGINEER				CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEERS OFFICE, YORK.		
2	REDRAWN WAS PREVIOUSLY DRG. NO. 100309 SHT. 7.			CORR. REF.		TS 1153/3A		UNIVERSAL CONCENTRATOR		
				AUTHORITY				BRACKET & SPACERS		
				DATE		4-3-71		FOR		
				H.O. BALDWIN <i>for [Signature]</i>				BACKSTRIP MOUNTING		
								SHEET 18 OF 23 SHEETS		ISSUE
								DRG. NO. 100999		1 2



ISSUE		App	COMP	DRN.	K.H. J.F.	Chkd.	BRITISH RAILWAYS		E. REGION	
1	-	-	-	ASS'T TELECOMMS. ENGINEER			CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER'S OFFICE, YORK. UNIVERSAL CONCENTRATOR PICTORIAL VIEW OF EXTN. CARD & SOCKET		SHEET 22 OF 23 SHEETS DRG. No. 100999	
2	REDRAWN WAS PREVIOUSLY DRG. No 100309 SHT 10.			CORR. REF.	TS1153/3A					
				AUTHORITY						
				DATE						
H.O. BALDWIN <i>[Signature]</i> Chief Signal and Telecommunications Engineer							ISSUE 1 2			



NOTES:

- NEGATIVE IS FROM CONCENTRATOR BATTERY
- C IS $1.25 \mu F$ 250V W.
- THIS IS TO BE MOUNTED INDEPENDENT OF THE CONCENTRATOR

ISSUE		APP	COMP	DRN	DES	CHKD	KH	BRITISH RAILWAYS	E. REGION
1	-	-	-	ASS'T TELECOMMS ENGINEER				CHIEF SIGNAL & TELECOMMUNICATIONS ENGINEER'S OFFICE, YORK.	
2	REDRAWN. WAS PREVIOUSLY DRG. NO. 100939 SHT 4			CORR REF	TS 53 3A			UNIVERSAL CONCENTRATOR S.T.C. CONTROL ARRANGEMENT	
				AUTHORITY					
				DATE					
				H. O. BALDWIN <i>[Signature]</i> Chief Signal and Telecommunications Engineer				SHEET 23 OF 23 SHEETS	
								ISSUE	
				DRG. No. 100999				1 2	