

CB & AUTOMATIC SYSTEMS  
SUBSCRIBER'S EXTENSION PLAN 1 (INTERNAL ONLY)  
ON EXTERNAL EXTENSION OF PLAN 7 OR 7A  
USING TELEPHONES Nos. 326 CB & 328...

N4333  
2 PANELS-1  
24-8-54

CB & AUTO

NOTES

GENERAL

1. THE DIAGRAM SHOWS A PLAN 1 EXTENSION CONNECTED TO THE EXTERNAL EXTENSION OF A PLAN 7 OR 7A.
2. FOR AUTOMATIC WORKING USE APPROPRIATE TELEPHONE.  
eg. TELEPHONE No. 328F.  
REMOVE STRAP DS4-DS5 IN TELE No. 326CB, FIT DIAL, AUTO No. 12... & CORD, INST. 5/28E. 5"

PLAN 7 OR 7A EXTERNAL EXTENSION

3. FIT CORD, INST. No. 4/57B... TO BLOCK, TERMINAL No. 20/8 & TO TELEPHONE No. 328... FIT KEY No. 302A WITH ONE PART No. 1/SPL/325 (PLUNGER) IN TELEPHONE. THE LEVER SPRING OF KEY No. 302A SHOULD BE CONNECTED TO T1 & THE MAKE SPRING CONNECTED TO T3; STRAP T1-T2; FIT LABEL No. 252A ON TELEPHONE.
4. PROVIDE 2 CELLS LECLANCHÉ DR2 AND CONNECT WITH 2W CABLE BETWEEN BT6-BT7.
5. FIT CORD, INST. No. 3/62B... TO GENERATOR No. 26 AP.

PLAN 1 EXTENSION

6. FIT CORD, INST. No. 4/57B... & BLOCK, TERMINAL No. 20/8 TO TELEPHONE, No. 326CB.  
DISCONNECT STRAP T10-T11 AND ADD STRAP T1-T2.  
CONNECT BELL No. 65A COILS IN PARALLEL.
7. FIT CORD, INST. No. 3/62B... TO GENERATOR No. 26 AP.

Amount

PAPER  
W

PLAN 7 OR 7A, EXTERNAL EXTENSION

PLAN I EXTENSION

